

## Technical indicators

Accuracy class: 0.5

Signal input:

AC ammeter AC 0-5A(CT\*\*)(5A)

DC ammeter DC 0-5A (Shunt\*\*)(75mV)

AC voltmeter AC 0-600V(PT\*\*)(180V)

DC voltmeter DC 0-600V

Auxiliary power: AC 220V,50/60Hz (can customize other values)

Outline drawing unit:mm



Model and Specification

Function Model	Measuring functions		
	Voltage	Current	Frequency
SF0-GK1-U	■		
SF0-GK1-I		■	
SF0-GK1-F			■